

**RECOMMENDED RS485 CONVERTERS FROM B&B ELECTRONICS ([www.bb-elec.com](http://www.bb-elec.com))**




**485SD9R** - For use on any system with a standard DB9 RS232 port. Port powered.

**OR**



**485USB9F-2W** - For use on a PC that has a USB port. Port powered.

**A DB9-RJ45 ADAPTER IS REQUIRED FOR EASE OF CONNECTION TO THE SDN BUS**



B&B ELECTRONICS #9M8CK  
OR EQUIVALENT

**RJ45 wire colors:**

- 1-Blue
- 2-Orange
- 3-Black
- 4-Red
- 5-Green
- 6-Yellow
- 7-Brown
- 8-White

(Female Gender)



RJ45  
8x8

Pinout for **ONLY** B&B models 485SD9R & 485USB9F-2W:

<u>DB9</u>		<u>RJ45</u>
Pin 2 - RS485 (- or "A")	→	Pin 2 Orange
Pin 3 - RS485 (+ or "B")	→	Pin 1 Blue
Pin 4 - RS485 (GND)	→	Pin 7 Brown
Pin 6 - RS485 (GND)	→	Pin 8 White
Note: Cut off unused pins !!		